

**Digital input interface (end of life)**
**TDS12128**


Interface to be connected on the AUTOBUS. This interface has 8 voltage free contact inputs. These are to be used to connect for example push buttons (any brand), window contacts, etc.

The interface is a built in type for in-wall mounting.

<b>Application:</b>		Built in interface for up to 8 voltage free digital input contacts.
<b>Characteristics:</b>	Inputs:	Possibility to connect 8 voltage free contacts (low frequency max 1Hz)
	IR:	Possibility to connect an IR receiver (optional TDS12129)
<b>Settings:</b>	Functions:	Through PROSOFT
	AUTOBUS address:	Trough rotary switches ROT1 + ROT2: MICROS: from 6 to 25 COMPACT: from 01 to 40 PROJECT: from 01 to 99
	Jumpers:	JP1+JP2: baudrate (standard 9600) JP3: terminating resistor (stand. off)
<b>Installation:</b>		Built-in
<b>Connections:</b>	AUTOBUS:	By enclosed AUTOBUS connector
	IR-link:	By enclosed AUTOBUS connector (green wire)
<b>Dimensions:</b>	Dimensions	Width: 90; height: 45; depth: 15 (in mm)
	Weight	0,160 kg
<b>Schematic Drawing:</b>		

